



Strobe Light and Annunciator

Performance: Blazon/3 is triggered by the same voltage which lights the normal signal lamps in the intercom system. Whenever any signal lamp button on any station in the same circuit is pressed, the Blazon/3 will be activated. The xenon lamp is permanently connected. The audible annunciator may be switched among constant, pulsed, and off. Circuitry is provided to sustain the Blazon/3 for 4 seconds after being triggered. The xenon lamp has a flash rate of 2Hz, providing 8 flashes per cycle.



The Blazon/3 is connected to the headset intercom system in the same manner as a belt pack. It has two 3-pin XLR connectors on the rear panel. By convention (to differentiate from microphone inputs) the female connector is designated as input. The male connector is provided for looping onwards to the next station in the system. Reversing these connections will not affect operation.

Blazon/3 is powered by the intercom power supply and requires no batteries or other external power source. In its ready mode it draws only 21.1mA; with the strobe active, 56mA, and; with the strobe and audible annunciator, only 108mA. When calculating power supply requirements, you may consider the Blazon/3 as the approximate equivalent of 3 or 4 belt packs.

Durability: The ribbed, extruded aluminum case; glass-filled nylon end bezels; internal support system for the PC board, and; best quality XLR-type connectors, all contribute to the Blazon/3's ability to withstand rough usage.

Value: The comparatively low price of the Blazon/3 is made possible by the minimized assembly cost resulting from simplicity of construction.

Compatibility: Blazon/3 is compatible with Clear-Com[®] and other lesser known (unbalanced 200Ω) headset intercom systems.

Technical specifications: (Subject to change without notice)

Supply voltage: 24 ~ 30 VDC nominal
 Switch-on voltage: 8 Volts minimum
 Switch-off voltage: 5 Volts maximum
 Switch-on time: 75 milliseconds
 Switch-off time: 4 seconds

Flash rate: 2Hz / Flash power: 0.75 joules
 Input impedance: 1 Meg Ω
 Power consumption: Ready - 21.1mA
 Strobe only - 56 mA Strobe & Annunciator - 108mA
 Size: 3.70x4.30x5.80 in. (93.98x109.22x147.32 mm)
 Weight 20oz. (0.567Kg)

Production Intercom Inc.

P.O. Box 3247, Barrington, IL 60011-3247
 Voice: (847) 381-5350 Fax: (847) 381-4360 Sales & Technical Assistance (US & Can): (800) 562-5872
 e-mail: support@beltpack.com Web: beltpack.com